E2000 ADAPTER - DATASHEET

Posted on 25-06-2024 by barpaadminuser

ADAPTER
E2000

DESCRIPTION

High reliability and precision alignment. Easy to use. Can be widely used for FTT, passive optical network (OPN) and cable TV network (CATV). Low Insertion loss and return loss. Good repeatability, changeability and temperature stabilization. Include dust protections caps. Allow fitting in the bulkheads patch panel either with a nut or with clips.



E2000/APC SIMPLEX



E2000/APC - SC/APC SIMPLEX



E2000 SIMPLEX

APPLICABLE STANDARDS

• ISO/IEC 11801 • EN 50173-1 • IEC 61754-20 • IEC 61753-1 • IEC 61300 • RoHS

ROHS

25 YEARS WARRANTY

OPERATING PERFORMANCE

	Singlemode	
	UPC	APC
Insertion Loss (dB)	< 0,3	< 0,3
Durability (500 Mating) (dB)	< 0,2	< 0,2
Operation Temperature (°C)	-40 to +85	-40 to +85
Retention Force (N)	200-600	200-600
Housing Material	PEI (PBT)	PEI (PBT)
Mounting Style	Screws	Screws
Sleeve Material	Ceramics (Grade A)	Ceramics (Grade A)
Colour	Blue	Green

This document is authored and owned by barpa . It is forbidden to reproduce in whole or in part without mentioning it's authorship, as well as modification of its content or context. All specifications are subject to change without notice.
The pictures/drawings are mainly illustrative.
More information: info@barpa.eu or in www.barpa.eu