

DESCRIPTION

The barpa Power Distribution Unit is fitted for racks and/or networking equipment. It's designed to supply electric power in a very demanding and challenging environment as data center.

APPLICABLE STANDARDS

• IEC/EN 60884-1 • EIA 310



SPECIFICATIONS

Ranges of Electrical Information	Current Rating (A)	10 - 16		
	Voltage Rating (V)	110 - 250		
	Power Rating (W)	1800 - 3800		
	Frequency (Hz)	50 - 60		
		Flame retardant PC		
Material	Copper bar			
	Aluminum alloy shell			
	Metal bracket			
Cable Property	H05VV-F3Gx1,5mm²			
Cable Length (m)		1,8		
Work Temperature (°C)		-10 to 45		
Product Color	Black			
Control System	Without Switch , Switch, Circuit Breaker, Switch & Surge Protection			
Protection Sytem	Assembled with Children Protectors			
Number of U's	1			

NUMBER OF SOCKET

Horizontal	3 Ways / 6 Ways / 8 Ways / 9 Ways / 12 Ways
Vertical	8 Ways / 12 Ways / 16 Ways

This document is authored and owned by barpa . It is forbidden to reproduce in whole or in part without mentioning its authorship, as well as modification of its content or context. All specifications are subject to change without notice. The pictures/davning are merely illustrative. More information: info@barpa.eu or in www.barpa.eu

barpa POWER DISTRIBUTION UNIT HORIZONTAL / VERTICAL


TYPE					
	SCHUKO	\odot			
_	FR	$\mathbf{\dot{o}}$			
	UK				
Plug Type —	П	$\langle \bullet \bullet \bullet \rangle$			
	IEC				
	US (Type B)				
_	SCHUKO	\odot			
	FR	\odot			
Socket Type —	UK				
Socket Type	П	•••			
	IEC				
	US (Type B)				


ORDER INFORMATION

Number of Sockets	Code	Width	Туре	Control System	Socket Type	Plug Type	Eletrical Information	Unit Weight (kg
3 8238103114	82384031000	10"	Horizontal	Switch	Schuko	Schuko	16A, 250V, 3500W	0,500
	82381031141			-		US (B)	15 4 1101/ 1/ 5014/	0,550
	82381031101			Switch	- US (B)		15A, 110V, 1650W -	0,570
8	82381061000			Switch			1/ 4 2501/ 250014/	0,800
	82381061020		-	Circuit Breaker	Schuko	Schuko	16A,250V, 3500W	0,875
	82381061050		_ Horizontal	Switch & Surge Protection		Schoko	16A,250V, 3800W	0,875
	82381061100				US (B)	Schuko	15A,120V,1800W	0,750
6	82381061200	19"			UK	Schuko	124 2501/ 225014/	0,700
-	82381061202			Switch	UK	UK	– 13A,250V, 3250W –	0,710
	82381061300				French	French	16A, 250V, 3500W	0,800
	82381061400				Italian	Schuko	10/16A,250V, 3500W	0,800
_	82381061141		-	-			15A, 110V, 1650W -	0,600
	82381061101			Switch	— US (B)	US (B)		0,630
	82381081202	-	Vertical	Switch	UK	UK	13A,250V, 3250W	0,750
	82381081000			Switch		<u> </u>		0,875
0	82381081040	- 19″	-	-	– Schuko	Schuko	16A,250V, 3500W	0,750
8	82381081303		Horizontal	Switch	French	French		0,880
	82381081141		=	-			US (B) 15A, 110V, 1650W -	0,750
	82381081101		=	Switch	– US (B)	US (B)		0,780
0	82381091700	10"		Switch	Schuko +		0,850	
9	82381091740	19″	Horizontal -	-	3IEC		10/ 16A,250V, 3500W -	0,800
	82381121505	19″	Horizontal	Switch	IEC C13	IEC C14	10A,250V, 2500W	0,800
12	82381122000	-		Switch	Schuko	Schuko	16A 250V,3500W	1,100
	82381122101	-	Vertical	Switch				0,880
	82381122141	-		-	US (B)	US (B)	15A, 110V, 1650W	0,850
	82381162000	-		Switch	Schuko	Schuko	16A 250V, 3500W	1,100
16	82381162141	-	Vertical	-			15A, 110V, 1650W –	1,000
	82381162101	-		Switch	US (B)	US (B)		1,030

Note: For inquiries regarding the surge protection option, please contact our sales support team.

This document is authored and owned by barpa . It is forbidden to reproduce in whole or in part without mentioning its authorship, as well as modification of its content or context. All specifications are subject to change without notice. The pictures/davings are merely illustrative. More information: info@barpa.eu or in www.barpa.eu





			Inner	Box	Outer	Box
Туре	Width	Unit Dimensions (mm)	Dimensions (mm)	Quantity (un)	Dimensions (mm)	Quantity (un)
	10"	273x44,4x45,5	280x95x55	1	493x300x235	
Horizontal —	19"	438x44,4x45,5	505x95x55		520x400x290	20
		659x45,4x45,5	700x95x55		720x400x290	20
Vertical	-	844x45,4x45,5	820x95x55		820x400x290	


TECHNICAL DRAWING (mm)

5,5

Please consider the general measures of the products.

Through the table, consider the number of sockets, the type of sockets and whether or not there is a switch.

HORIZONTAL



POWER DISTRIBUTION UNIT HORIZONTAL / VERTICAL

82384031000



82381031101




















82381081000




82381081040



82381061300



82381081303



82381061400

This document is authored and owned by barpa . It is forbidden to reproduce in whole or in part without mentioning its authorship, as well as modification of its content or context. All specifications are subject to change without notice. The pictures/davings are merely illustrative. More information: info@barpa.eu or in www.barpa.eu 45,5

0


45,5

45,5

45.5

45,5








45.5

82381061200 // 82381061202




82381061020



82381061141 // 82381061101 // 82381061100



82381081141 // 82381081101



82381091700 // 82381091740



82381121505

This document is authored and owned by barpa . It is forbidden to reproduce in whole or in part without mentioning its authorship, as well as modification of its content or context. All specifications are subject to change without notice. The pictures/davning are merely illustrative. More information: info@barpa.eu or in www.barpa.eu

45,5	
•	
0	


45,5	
0	
0	








VERTICAL



This document is authored and owned by barpa . It is forbidden to reproduce in whole or in part without mentioning its authorship, as well as modification of its content or context. All specifications are subject to change without notice. The pictures/drawings are merely illustrative. More information: info@barpa.eu or in www.barpa.eu







82381081202

PACKAGING

This images are merely illustratives. We want you to see the importance we attach to the packaging. We always work with products and materials that are easy to use.

